LCD5802D

40 CH 5.8GHz Diversity LCD Screen Receiver Monitor with DVR

Specification:

☆ Built-in 5.8Ghz Dual diversity receiver automatically for best reception

☆ Built-in 2CH 5.8Ghz AV output and ICHAV input

☆Built-in high performance Li-POLYMER Battery 2000mAH/7.4V

☆ Work status OSD display:RSSI indication;Battery indicator;Channel indication

☆A key to automatic signal search

☆ Support Chinese and English menu

☆ Size:180mm×120mm×50mm(Notc:Sunshield height:28mm)

☆ Working Voltage:DC7-16V

☆Power Consumption:max650 mA@12V

☆ Battery charging current:850 mA@12V(max)

☆Working temperature:-10℃~+65℃

Features:

☆ Built-in Dual Receiver Automatically for best reception Automatic Antenna Switching

☆Dual bufferred AV outputs

☆Not affect by 2.4GHz R/C Radios

☆AV Receiver with Diversity inputs

☆Small,light weight,durable

☆5 Bands and total 40 Channels

☆ Built -in battery,easy to carry and outdoor use

☆A key to automatic signal search,Simple operation

☆Work status OSD display:Always be aware of the device working condition.

Dispaly Parameters

☆ Screen size:7"

☆Screen type:TFT LCD Screen/long life,LED backlight

☆Resolution:800×480

☆Brightness:600cd/m2

☆View Angle:140/120 degree(Horizontal/Vertical)

2.JACK

1)AV OUT:Output of an AV signal.

2)TF card.

3)AV in:input Audio and Video Signal.

4)DC/+12VDCIN,+12V power supply,the device operating current of 650 mA@12V, built- in battery maximum charge current of 800 mA@12V;if the device is working when charging please pay attention to selecting the rated current greater than 2A/12V charging equipment.

3.Battery

Built-in 7.4V 2000mAH high-capacity polymer battery,when the battery is charging,the device where the lower left corner labeled cells,the red LED will ight when charging is completed,here are bright green LED;

4.DVR

*Enter DVR

Call MENU and select DVR (Long Press MENU button to call menu,and use Band+ Button to select DVR mode)

*Review/Replay DVR mode

Buttons have different function in DVR mode

*Record file:AVI,720*480px Progressive

*Support up to 32G card(C10 recommend).



K1:Quit DVR mode(Quit DVR review/delete mode)

K2:Delete

K3:Up/Stop,if it is replaying(Select a file,can be a picture or a video)

K4:Down(Select a file,can be a picture or a video)

K5:Play/Pause (for reviewing video)

Note: If the device is not used for a long time,Please charged once every four months,in order to protect the battery.

Band and Channel selection

CH / GROUP	CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8
A	5865MHz	5845MHz	5825MHz	5805MHz	5785MHz	5765MHz	5745MHz	5725MHz
B	5733MHz	5752MHz	5771MHz	5790MHz	5809MHz	5828MHz	5847MHz	5866MHz
C	5705MHz	5685MHz	5665MHz	5645MHz	5885MHz	5905MHz	5925MHz	5945MHz
D	5740MHz	5760MHz	5780MHz	5800MHz	5820MHz	5840MHz	5860MHz	5880MHz
R	5658MHz	5695MHz	5732MHz	5769MHz	5806MHz	5843MHz	5880MHz	5917MHz

Operation Instructions

KEY

1)BAND+

Default mode,click the BAND+option,A,B,C,D cycle selection;

MENU pressed,this button is used as number+.

2)CH+

Default mode,click the option for the CH1-8 cycles;MENU pressed,this button is used as the value-.

3)MENU/SRC

Long press,start to MENU.

Short press turn source.

LCD display parameter adjustment,where the parameters using +,- to adjust,click MENU, choose a different adjustment items.

DIVERSITY:true diversity reception mode,A and B the signal strength of a display,to achieve the best radio reception;corresponding to the A and B indicator LED will flash alternately.

A:A single received signal.

B:B single received sign

4)SEARCH

Press this button to enter the signal search,it will automatically search for the signals to a certain signal strength and stops on that channel. If the signal is not found,it will be on the channel before starting the search stopped;in searching process,all the buttons will not operate;

5) Rec/Pic:

□ Short press the button---A flash of the icon on right-up means: take a picture

● Long press the button---Red dot show up on right-up corner:Recording;

Red dot disappear when you press the Rec/Pic button again to save the video.

6) ⏻ : Press 0.5S boot,then press 0.5S shutdown.